

# EEE235F Class Test

20 May 2005

Name:

Student number:

---

## Information

- The test is closed-book.
  - This test has *three* questions, totalling 30 marks.
  - Answer *all* the questions.
  - You have 45 minutes.
  - There is an information sheet attached to the end of this question paper.
- 

1. (10 marks) Use time-domain convolution to find the inverse Fourier transform of

$$X(\omega) = \frac{1}{(a + j\omega)^2}.$$

The signal

$$X(\omega) = \frac{1}{(a + j\omega)} \frac{1}{(a + j\omega)} = X_1(\omega)X_1(\omega)$$

where  $X_1(\omega)$  has inverse transform (from tables)

$$x_1(t) = e^{-at}u(t).$$

Multiplication in the frequency domain corresponds to convolution in the time domain, so

$$\begin{aligned} x(t) &= x_1(t) * x_1(t) = \int_{-\infty}^{\infty} x_1(\tau)x_1(t - \tau)d\tau = \int_{-\infty}^{\infty} e^{-a\tau}u(\tau)e^{-a(t-\tau)}u(t - \tau)d\tau \\ &= \int_0^t e^{-a\tau}e^{-a(t-\tau)}d\tau = e^{-at} \int_0^t d\tau = te^{-at}u(t). \end{aligned}$$

---

2. (10 marks) A time signal  $x(t)$  has the Fourier transform  $4/(4 + \omega^2)$ . Find the Fourier transforms of the following signals:

(a)  $x_1(t) = x(2t - 3)$

(b)  $x_2(t) = \int_{-\infty}^t x(\tau) d\tau$ .

(a) Given

$$x(t) \longleftrightarrow \frac{4}{4 + \omega^2},$$

frequency scaling gives

$$x(2t) \longleftrightarrow \frac{1}{2} \frac{4}{4 + (\frac{\omega}{2})^2} = \frac{2}{4 + (\frac{\omega}{2})^2}.$$

Finally a time shift of 3/2 gives the required transform pair:

$$x(2t - 3) = x(2(t - 3/2)) \longleftrightarrow \frac{2}{4 + (\frac{\omega}{2})^2} e^{-j\omega 3/2}.$$

(b) The integration property states that

$$\int_{-\infty}^t x(\lambda) d\lambda \longleftrightarrow \frac{1}{j\omega} X(\omega) + \pi X(0) \delta(\omega),$$

so

$$\begin{aligned} x_2(t) = \int_{-\infty}^t x(\lambda) d\lambda &\longleftrightarrow \frac{1}{j\omega} \frac{4}{4 + \omega^2} + \pi \frac{4}{4 + 0^2} \delta(\omega) \\ &\longleftrightarrow \frac{1}{j\omega} \frac{4}{4 + \omega^2} + \pi \delta(\omega) \end{aligned}$$


---

3. (10 marks) Find the inverse Fourier transform of the signal

$$G(\omega) = \frac{1}{1 + j\omega} \cos(2\omega) e^{-j5\omega}.$$

We can write

$$G(\omega) = \frac{1}{1 + j\omega} \frac{1}{2} (e^{j2\omega} + e^{-j2\omega}) e^{-j5\omega} = \frac{1}{2} \frac{1}{1 + j\omega} e^{-j3\omega} + \frac{1}{2} \frac{1}{1 + j\omega} e^{-j7\omega}.$$

Now

$$e^{-t} u(t) \longleftrightarrow \frac{1}{1 + j\omega},$$

so

$$\frac{1}{2} e^{-t} u(t) \longleftrightarrow \frac{1}{2} \frac{1}{1 + j\omega}$$

and

$$\frac{1}{2} e^{-(t-3)} u(t-3) \longleftrightarrow \frac{1}{2} \frac{1}{1 + j\omega} e^{-j3\omega}$$

$$\frac{1}{2} e^{-(t-7)} u(t-7) \longleftrightarrow \frac{1}{2} \frac{1}{1 + j\omega} e^{-j7\omega}$$

Therefore the inverse is

$$g(t) = \frac{1}{2} e^{-(t-3)} u(t-3) + \frac{1}{2} e^{-(t-7)} u(t-7).$$


---

## INFORMATION SHEET

### Fourier transform properties

| Property                              | Transform Pair/Property  |
|---------------------------------------|--|
| Linearity                             | $ax(t) + bv(t) \leftrightarrow aX(\omega) + bV(\omega)$  |
| Time shift                            | $x(t - c) \leftrightarrow X(\omega)e^{-j\omega c}$   |
| Time scaling                          | $x(at) \leftrightarrow \frac{1}{ a }X\left(\frac{\omega}{a}\right) \quad a > 0$  |
| Time reversal                         | $x(-t) \leftrightarrow X(-\omega) = \overline{X(\omega)}$  |
| Multiplication by power of $t$        | $t^n x(t) \leftrightarrow j^n \frac{d^n}{d\omega^n} X(\omega) \quad n = 1, 2, \dots$   |
| Multiplication by complex exponential | $x(t)e^{j\omega_0 t} \leftrightarrow X(\omega - \omega_0) \quad \omega_0 \text{ real}$   |
| Differentiation in time domain        | $\frac{d^n}{dt^n} x(t) \leftrightarrow (j\omega)^n X(\omega) \quad n = 1, 2, \dots$  |
| Integration                           | $\int_{-\infty}^t x(\lambda) d\lambda \leftrightarrow \frac{1}{j\omega} X(\omega) + \pi X(0)\delta(\omega)$                      |
| Convolution in time domain            | $x(t) * v(t) \leftrightarrow X(\omega)V(\omega)$   |
| Multiplication in time domain         | $x(t)v(t) \leftrightarrow \frac{1}{2\pi} X(\omega) * V(\omega)$  |
| Parseval's theorem                    | $\int_{-\infty}^{\infty} x(t)v(t)dt \leftrightarrow \frac{1}{2\pi} \int_{-\infty}^{\infty} \overline{X(\omega)}V(\omega)d\omega$ |
| Duality                               | $X(t) \leftrightarrow 2\pi x(-\omega)$   |

### Common Fourier Transform Pairs

| $x(t)$   | $X(\omega)$   |
|--|---|
| 1 $(-\infty < t < \infty)$                     | $2\pi\delta(\omega)$  |
| $-0.5 + u(t)$                                  | $\frac{1}{j\omega}$   |
| $u(t)$   | $\pi\delta(\omega) + \frac{1}{j\omega}$                                     |
| $\delta(t)$                                    | 1   |
| $\delta(t - c)$                                | $e^{-j\omega c} \quad (c \text{ any real number})$                          |
| $e^{-bt}u(t)$                                  | $\frac{1}{j\omega + b} \quad (b > 0)$                                       |
| $e^{j\omega_0 t}$                              | $2\pi\delta(\omega - \omega_0) \quad (\omega_0 \text{ any real number})$    |
| $p_\tau(t)$                                    | $\tau \operatorname{sinc} \frac{\tau\omega}{2\pi}$                          |
| $\left(1 - \frac{2 t }{\tau}\right) p_\tau(t)$ | $\frac{\tau}{2} \operatorname{sinc}^2 \left(\frac{\tau\omega}{4\pi}\right)$ |