

# EEE2035F: Signals and Systems I

## Class Test 1

19 March 2012

Name:

Student number:

---

### Information

- The test is closed-book.
  - This test has *four* questions, totalling 25 marks.
  - Answer *all* the questions.
  - You have 45 minutes.
- 

1. (10 marks) Suppose  $x(t) = e^{-t}u(t)$ . Sketch the following:


- (a)  $y_1(t) = x(t)$
- (b)  $y_2(t) = x(-t + 1)$
- (c)  $y_3(t) = x(-t + 1)u(t)$
- (d)  $y_4(\lambda) = x(t - \lambda)$
- (e)  $y_5(t) = x(t)\delta(t - 1)$
- (f)  $y_6(t) = \frac{d}{dt}x(t)$

2. (5 marks) Suppose the output  $y(t)$  of a system is related to the input  $x(t)$  via the relationship


$$y(t) = x(t) + 1.$$

- (a) Is the system linear?
- (b) Is the system time invariant?

3. (5 marks) Suppose you're given the signals



- (a) Use the method of your choice to find  $w(t) = x(t) * y(t)$ .
- (b) Use the result from the previous question to find  $f(t) = y(t) * v(t)$  for these signals:



4. (5 marks) A unit step input is applied to a LTI system, and results in the following response:

$$y(t) = \frac{1}{2}tu(t) - \frac{1}{20}(1 - e^{-10t})u(t).$$

- (a) Find and plot  $\frac{d}{dt}y(t)$ .
- (b) Use the derivative property of convolution to find the impulse response of the system.