

EEE4001F: Digital Signal Processing

Class Test 1

22 March 2007

Name:

Student number:

Information

- The test is closed-book.
 - This test has *four* questions, totalling 20 marks.
 - Answer *all* the questions.
 - You have 45 minutes.
-

1. (5 marks) Determine the impulse response of the LTI system described by the difference equation

$$y[n] - 0.2y[n - 1] = x[n] + 0.5x[n - 1]$$

under the assumption that it is causal. Is the system stable?

2. (5 marks) Which of the impulse responses

$$h_1[n] = 3\delta[n - 2] + \delta[n - 4]$$

$$h_2[n] = u[n - 3] - u[n + 5]$$


describe causal, stable, LTI processors? Give reasons for your answers. Sketch the step response of each system.

3. (5 marks) Convolve the signals

$$x_1[n] = \delta[n] - \delta[n - 2] + \delta[n - 3] \quad \text{and} \quad x_2[n] = 2\delta[n - 1] + \delta[n - 2] - \delta[n - 3]$$

using the z-transform.

4. (5 marks) Suppose $y[n]$ is the output of an LTI system when $x[n]$ is the input:



Find the response of the system to the input

