

# EEE4001F: Digital Signal Processing

## Class Test 1

20 March 2015

Name:


Student number:

---

### Information

- The test is closed-book.
  - This test has *four* questions, totalling 20 marks.
  - Answer *all* the questions.
  - You have 45 minutes.
  - An information sheet is attached.
- 

1. (5 marks) Suppose  $x[n]$  is as given below:



Plot the following:

- $y_1[n] = x[2n]$
- $y_2[n] = x[2n - 1]$
- $y_3[n] = x[n] - x[n - 1]$
- $y_4[n] = \sum_{k=-\infty}^n x[k]$
- $y_5[n] = x[n] * u[n]$ .

2. (5 marks) A linear time-invariant system with impulse response  $h[n] = a^{-n}u[-n]$  (for  $0 < a < 1$ ) is driven by the unit step input  $x[n] = u[n]$ . Sketch the signals  $h[n]$  and  $x[n]$  and find the output  $y[n] = h[n] * x[n]$  for values  $n = 2$  and  $n = -2$ .

3. (4 marks) Find a closed-form expression for the frequency response  $H(e^{j\omega})$  of the FIR filter with impulse response

$$h[n] = a^n(u[n] - u[n - 10]).$$

Is the filter causal? Why?

4. (6 marks) A causal digital filter with input  $x[n]$  and output  $y[n]$  is governed by the relationship

$$y[n] = x[n] + x[n-2] + y[n-1] - 0.5y[n-2].$$

- (a) Show that the system function can be written as

$$H(z) = \frac{z^2 + 1}{(z - z_0)(z - z_0^*)}$$

where  $z_0 = (1 + j)/2$  and  $z_0^*$  is the complex conjugate of  $z_0$ .

- (b) Sketch the poles and zeros of this filter in the  $z$ -plane.  
 (c) Determine an expression for the impulse response of the filter. You may write your solution in terms of undetermined coefficients along with a set of simultaneous equations that specify them.  
 (d) Is the filter stable?

## Fourier transform properties

| Sequences $x[n], y[n]$ | Transforms $X(e^{j\omega}), Y(e^{j\omega})$                                       | Property        |
|------------------------|---|-----------------|
| $ax[n] + by[n]$        | $aX(e^{j\omega}) + bY(e^{j\omega})$   | Linearity       |
| $x[n - n_d]$           | $e^{-j\omega n_d} X(e^{j\omega})$   | Time shift      |
| $e^{j\omega_0 n} x[n]$ | $X(e^{j(\omega - \omega_0)})$   | Frequency shift |
| $x[-n]$                | $X(e^{-j\omega})$   | Time reversal   |
| $nx[n]$                | $j \frac{dX(e^{j\omega})}{d\omega}$   | Frequency diff. |
| $x[n] * y[n]$          | $X(e^{-j\omega})Y(e^{-j\omega})$  | Convolution     |
| $x[n]y[n]$             | $\frac{1}{2\pi} \int_{-\pi}^{\pi} X(e^{j\theta})Y(e^{j(\omega - \theta)})d\theta$ | Modulation      |

## Common Fourier transform pairs

| Sequence   | Fourier transform  |
|--|--|
| $\delta[n]$  | 1  |
| $\delta[n - n_0]$  | $e^{-j\omega n_0}$   |
| 1 ( $-\infty < n < \infty$ )   | $\sum_{k=-\infty}^{\infty} 2\pi\delta(\omega + 2\pi k)$  |
| $a^n u[n]$ ( $ a  < 1$ )   | $\frac{1}{1 - ae^{-j\omega}}$  |
| $u[n]$   | $\frac{1}{1 - e^{-j\omega}} + \sum_{k=-\infty}^{\infty} \pi\delta(\omega + 2\pi k)$                      |
| $(n+1)a^n u[n]$ ( $ a  < 1$ )  | $\frac{1}{(1 - ae^{-j\omega})^2}$  |
| $\frac{\sin(\omega_c n)}{\pi n}$   | $X(e^{j\omega}) = \begin{cases} 1 &  \omega  < \omega_c \\ 0 & \omega_c <  \omega  \leq \pi \end{cases}$ |
| $x[n] = \begin{cases} 1 & 0 \leq n \leq M \\ 0 & \text{otherwise} \end{cases}$ | $\frac{\sin[\omega(M+1)/2]}{\sin(\omega/2)} e^{-j\omega M/2}$  |
| $e^{j\omega_0 n}$  | $\sum_{k=-\infty}^{\infty} 2\pi\delta(\omega - \omega_0 + 2\pi k)$                                       |

## Common z-transform pairs

| Sequence  | Transform   | ROC                          |
|---|---|------------------------------|
| $\delta[n]$   | 1   | All $z$                      |
| $u[n]$  | $\frac{1}{1-z^{-1}}$  | $ z  > 1$                    |
| $-u[-n-1]$  | $\frac{1}{1-z^{-1}}$  | $ z  < 1$                    |
| $\delta[n-m]$   | $z^{-m}$  | All $z$ except 0 or $\infty$ |
| $a^n u[n]$  | $\frac{1}{1-az^{-1}}$   | $ z  >  a $                  |
| $-a^n u[-n-1]$  | $\frac{1}{1-az^{-1}}$   | $ z  <  a $                  |
| $na^n u[n]$   | $\frac{az^{-1}}{(1-az^{-1})^2}$   | $ z  >  a $                  |
| $-na^n u[-n-1]$   | $\frac{az^{-1}}{(1-az^{-1})^2}$   | $ z  <  a $                  |
| $\begin{cases} a^n & 0 \leq n \leq N-1 \\ 0 & \text{otherwise} \end{cases}$ | $\frac{1-a^N z^{-N}}{1-az^{-1}}$  | $ z  > 0$                    |
| $\cos(\omega_0 n)u[n]$  | $\frac{1 - \cos(\omega_0)z^{-1}}{1 - 2\cos(\omega_0)z^{-1} + z^{-2}}$         | $ z  > 1$                    |
| $r^n \cos(\omega_0 n)u[n]$  | $\frac{1 - r \cos(\omega_0)z^{-1}}{1 - 2r \cos(\omega_0)z^{-1} + r^2 z^{-2}}$ | $ z  > r$                    |