

# EEE4001F: Digital Signal Processing

Class Test 1

11 March 2016

Name:

Student number:

---

## Information

- The test is closed-book.
  - This test has *four* questions, totalling 20 marks.
  - Answer *all* the questions.
  - You have 45 minutes.
  - An information sheet is attached.
-

1. (5 marks) A discrete-time system is governed by the following relation:

$$y[n] = \sum_{k=0}^2 x[n-k] + x[0].$$

- (a) Find the output when the input is  $x_1[n] = u[n]$ .
- (b) Find the output when the input is  $x_2[n] = u[n-1]$ .
- (c) Is the system time invariant?

2. (5 marks) Determine the DTFT of the sequence  $x[n] = \alpha^n u[-n - 1]$  for  $|\alpha| > 1$ .

3. (5 marks) Suppose a sequence  $x[n]$  has DTFT  $X(e^{j\omega})$ . Find the time-domain inverses of each of the following:

(a)  $Y_1(e^{j\omega}) = 2X(e^{-j(\omega-\omega_0)})$ , and

(b)  $Y_2(e^{j\omega}) = 3e^{j4\omega}X(e^{j(\omega-\omega_0)})$ .

Express your answers in terms of  $x[n]$ .

4. (5 marks) Consider two discrete-time systems with the following impulse responses:

$$h_1[n] = \delta[n] - \delta[n - 1] \quad \text{and} \quad h_2[n] = u[n].$$

- (a) Are the systems causal? Why?
- (b) Using time-domain reasoning show that the systems are inverses of one another.
- (c) Draw pole-zero plots of the system functions in each case.

## Fourier transform properties

Sequences $x[n], y[n]$	Transforms $X(e^{j\omega}), Y(e^{j\omega})$	Property
$ax[n] + by[n]$	$aX(e^{j\omega}) + bY(e^{j\omega})$	Linearity
$x[n - n_d]$	$e^{-j\omega n_d} X(e^{j\omega})$	Time shift
$e^{j\omega_0 n} x[n]$	$X(e^{j(\omega - \omega_0)})$	Frequency shift
$x[-n]$	$X(e^{-j\omega})$	Time reversal
$nx[n]$	$j \frac{dX(e^{j\omega})}{d\omega}$	Frequency diff.
$x[n] * y[n]$	$X(e^{-j\omega})Y(e^{-j\omega})$	Convolution
$x[n]y[n]$	$\frac{1}{2\pi} \int_{-\pi}^{\pi} X(e^{j\theta})Y(e^{j(\omega - \theta)})d\theta$	Modulation

## Common Fourier transform pairs

Sequence	Fourier transform
$\delta[n]$	1
$\delta[n - n_0]$	$e^{-j\omega n_0}$
1 $(-\infty < n < \infty)$	$\sum_{k=-\infty}^{\infty} 2\pi\delta(\omega + 2\pi k)$
$a^n u[n]$ $( a  < 1)$	$\frac{1}{1 - ae^{-j\omega}}$
$u[n]$	$\frac{1}{1 - e^{-j\omega}} + \sum_{k=-\infty}^{\infty} \pi\delta(\omega + 2\pi k)$
$(n + 1)a^n u[n]$ $( a  < 1)$	$\frac{1}{(1 - ae^{-j\omega})^2}$
$\frac{\sin(\omega_c n)}{\pi n}$	$X(e^{j\omega}) = \begin{cases} 1 &  \omega  < \omega_c \\ 0 & \omega_c <  \omega  \leq \pi \end{cases}$
$x[n] = \begin{cases} 1 & 0 \leq n \leq M \\ 0 & \text{otherwise} \end{cases}$	$\frac{\sin[\omega(M+1)/2]}{\sin(\omega/2)} e^{-j\omega M/2}$
$e^{j\omega_0 n}$	$\sum_{k=-\infty}^{\infty} 2\pi\delta(\omega - \omega_0 + 2\pi k)$

## Common z-transform pairs

Sequence	Transform	ROC
$\delta[n]$	1	All $z$
$u[n]$	$\frac{1}{1 - z^{-1}}$	$ z  > 1$
$-u[-n - 1]$	$\frac{1}{1 - z^{-1}}$	$ z  < 1$
$\delta[n - m]$	$z^{-m}$	All $z$ except 0 or $\infty$
$a^n u[n]$	$\frac{1}{1 - az^{-1}}$	$ z  >  a $
$-a^n u[-n - 1]$	$\frac{1}{1 - az^{-1}}$	$ z  <  a $
$na^n u[n]$	$\frac{az^{-1}}{(1 - az^{-1})^2}$	$ z  >  a $
$-na^n u[-n - 1]$	$\frac{az^{-1}}{(1 - az^{-1})^2}$	$ z  <  a $
$\begin{cases} a^n & 0 \leq n \leq N - 1, \\ 0 & \text{otherwise} \end{cases}$	$\frac{1 - a^N z^{-N}}{1 - az^{-1}}$	$ z  > 0$
$\cos(\omega_0 n)u[n]$	$\frac{1 - \cos(\omega_0)z^{-1}}{1 - 2\cos(\omega_0)z^{-1} + z^{-2}}$	$ z  > 1$
$r^n \cos(\omega_0 n)u[n]$	$\frac{1 - r\cos(\omega_0)z^{-1}}{1 - 2r\cos(\omega_0)z^{-1} + r^2 z^{-2}}$	$ z  >  r $